

Weather-Resistant Railnet[®]



Approximate Dimensions:

10 ft. long x 3 ft. high

To Use:

1. **Rolls Back From Sides:** The Railnet[®] can be rolled back from the side to shorten the width. Extra holes are provided along top and bottom edges for convenient fastening on ends when rolled back. Always tie through holes in binding, not net alone. Ties go through net and holes in binding to fasten end to wall or post.
2. **Rolls Up From Bottom:** The Railnet[®] can be rolled up from the bottom to shorten the height. Extra holes are provided along top and bottom edges for convenient fastening on ends when rolled back. Always tie through holes in binding, not net alone. Ties go through net and holes in binding to fasten bottom to floor or bottom rail.
3. **Lapped in Center:** The Railnet[®] can be lapped back upon itself to further shorten the width and be fastened at top and bottom by aligning the holes in binding. Tie through holes in binding only, not through net.
4. **Attaches to Floor if there is no Bottom Rail or Bottom Rail is too High Off Floor:** In cases where a bottom rail is eliminated in the railing design, or the bottom rail is not conveniently located, the Railnet[®] should be secured to floor by screw eyes. One screw eye is recommended per 6 inches (15.2 cm). Only 16 screw eyes are provided with this unit for use on ends. An additional 10 screws will be required to secure to floor. We recommend a 1.5" (3.81 cm) screw eye.